

MD300C2

Fingertip

Pulse Oximeter

Health Care from Choice**The Scope of Application**

Pulse oximeter is a very important and common device to check patient blood-oxygen saturation (SpO_2) level and pulse rate. As a small, compact, simple, reliable and durable physiological monitoring device, Fingertip pulse oximeter greatly enhances patient care. It is widely applied in clinic, hospital, social medical organizations, first aid and so on.

**Features:**

- Small & lightweight design (total 28g without batteries)
- Dual color OLED display
- Display SpO_2 , PR, Pulse bar and Plethysmogram
- 6 display modes
- Low power consumption, automatically power off
- Battery-low indicator
- 2 AAA alkaline or rechargeable batteries
- Adjustable brightness
- Accommodates widest range of finger sizes from pediatric to adult

6 Display modes:

Technical Specifications

Applicable Population

Adult, Pediatrics and Neonatal patients

SpO₂

Measurement range 70-100%
 Resolution 1%
 Measurement accuracy 80%-100%; $\pm 2\%$
 70%-79 %; $\pm 3\%$
 0%-69%;unspecified

Pulse Rate

Measuremet range 30-235 bpm
 Resolution 1bpm
 Measurement accuracy 30- 100; ± 2 bpm
 101- 235; $\pm 2\%$

Display

Type Dual color OLED display
 Parameters SpO₂, PR pulse bar
 Plethysmogram
 Mode 6 display modes
 Brightness Adjustable 10 levels

Alarm

Alarm Battery-low indicator

Mechanical

Dimension 58mm(W)×32mm(H)×34mm(D)
 Weight 28g (without batteries)

Battery

Type 2 AAA alkaline or rechargeable batteries
 Operation time about 30 hours for normal operation

Environmental

Operation Temperature 5℃-40℃
 Storage Temperature -20℃-55℃
 Operation Humidity RH \leq 85%
 Storage Humidity RH \leq 85%

Electromagnetic Compatibility

This product complies with IEC60601-1-2 for electromagnetic compatibility Class B

Interference Resistance Capacity against Ambient Light

Deviation is smaller than $\pm 1\%$ between values of Oxyhemoglobin measured in natural lighting indoor condition and present lighting sources and that measured in dark room.

AUTHORIZED AGENT



Health Care from Choice



Beijing Choice Electronic Technology Co., Ltd

Address: Bailangyuan Building B 1126-1128, Fuxing Road A36, Beijing, P. R. China Zip: 100039
 Tel: +86 10 88204188,88203520 FAX: +86 10 88204632
 Email: market@choicemed.com Website: www.choicemed.com